UNITED STATES PATENT APPLICATION

FOR

METHOD AND CIRCUIT FOR ALLOWING A MICROPROCESSOR TO CHANGE
ITS OPERATING FREQUENCY ON-THE-FLY

Inventors:

Bert S. Sullam

Prepared by:
WAGNER, MURABITO & HAO, LLP
Two North Market Street
Third Floor
San Jose, California 95113
(408) 938-9060

CYPR-CD00190

METHOD AND CIRCUIT FOR ALLOWING A MICROPROCESSOR TO CHANGE ITS OPERATING FREQUENCY ON-THE-FLY

CROSS REFERENCE TO RELATED DOCUMENTS

This application is related to and claims priority benefit of U.S. Provisional patent application serial no. 60/243,708, filed October 26, 2000, entitled "Advanced Programmable Microcontroller Device" to Snyder, et al., which is hereby incorporated herein by reference.

COPYRIGHT NOTICE

FIELD OF THE INVENTION

This invention relates generally to the field of providing clocking signals to microprocessors. More particularly, this invention relates to an apparatus and method for a processor to change the processor clock speed in a microcontroller on the fly.

BACKGROUND OF THE INVENTION

1
2 Microcontrollers are utilized in increasing numbers to carry out a wide range
3 of programmable operations. In some operations, perhaps especially those
4 requiring minimum power consumption, it is desirable for the microcontroller to be
5 able to change its own clock frequency. This is advantageous since reduced clock
6 speed usually translates to lower power consumption. The clock can be increased
7 in frequency when high computation power is required or when certain
8 microcontroller circuitry must operate at a high speed, and the power can be
9 reduced by reducing the clock speed at other times.

10 In order to effect a change in clock speed, a smooth speed transition should
11 take place in order to avoid clock "glitches" that can result in processor
12 malfunctions and even potentially lock up the circuitry. In addition, it is desirable
13 that any circuitry provided for manipulation of the clock speed should be simple and
14 occupy minimal die area in the finished microcontroller.

15

SUMMARY OF THE INVENTION

17 The present invention relates generally to clock circuits for integrated
18 processors. Objects, advantages and features of the invention will become
19 apparent to those skilled in the art upon consideration of the following detailed
20 description of the invention.

21 In one embodiment consistent with the present invention, a circuit that
22 permits a processor in a microcontroller to adjust its clock speed on the fly. A
23 processor receives a current clock signal and a phased current clock signal from
24 a speed selection switch. A new speed selection switch provides a new clock
25 signal and a phased new clock signal for comparison with the current clock
26 signals. When the states of the current and new clocks appropriately align after
27 issuance of a control signal from the processor, the new speed is switched into the
28 current speed switch to permit the clock speed to change without producing
29 spurious signals that can cause unpredictable action in the processor. This

1   advantageously allows the microcontroller to adjust its clock speed under program

2   control.

3   In an embodiment consistent with the present invention, a circuit that allows

4   a processor forming a part of a microcontroller to change its operating frequency

5   includes a clock generator generating a plurality of clock signals at a plurality of

6   frequencies. A first switch receives the plurality of clock signals and selects one

7   of the clock signals as an output thereof to be the current clock according to a

8   current speed select signal. A current speed latch stores the current speed select

9   signal. A first phase shifter shifts the phase of the current clock to produce a phase

10   shifted current clock. A second switch receives the plurality of clock signals and

11   selects one of the clock signals as an output thereof to be the new clock according

12   to a new speed select signal. A new speed register stores the new speed select

13   signal. The new speed select signal is produced by the processor and stored in the

14   new speed register. A second phase shifter shifts the phase of the new clock to

15   produce a phase shifted new clock. A logic circuit receives the current clock, the

16   phase shifted current clock, the new clock, the phase shifted new clock and a

17   signal from the processor directing a speed change as inputs thereto for producing

18   a signal latching the new speed into the current speed latch at a point in time after

19   the speed change signal when the current clock, phase shifted current clock, the

20   new clock and the phase shifted new clock have the same state.

21   A method for a processor forming a part of a microcontroller to change its

22   clock frequency consistent with an embodiment of the present invention, includes

23   at the processor, receiving a clock signal; determining that the clock frequency is

24   to be changed under program control; storing a new clock frequency signal in a

25   new speed register; issuing an I/O write command indicating that the clock

26   frequency is to change; in a logic circuit, examining a current clock signal, a new

27   clock signal, a phase shifted current clock signal and a phase shifted new clock

28   signal; when the current clock signal, the new clock signal, the phase shifted

29   current clock signal and the phase shifted new clock signal reach predetermined

30   states, latching the new clock frequency signal into a current clock speed latch;

1 and at a switch, receiving an output from the current clock speed latch and

2 changing a switch setting in response thereto, the switch setting determining the

3 speed of the clock signal.

4 The above summaries are intended to illustrate exemplary embodiments of

5 the invention, which will be best understood in conjunction with the detailed

6 description to follow, and are not intended to limit the scope of the appended

7 claims.

8

9 **BRIEF DESCRIPTION OF THE DRAWINGS**

10 The features of the invention believed to be novel are set forth with

11 particularity in the appended claims. The invention itself however, both as to

12 organization and method of operation, together with objects and advantages

13 thereof, may be best understood by reference to the following detailed description

14 of the invention, which describes certain exemplary embodiments of the invention,

15 taken in conjunction with the accompanying drawings in which:

16 FIGURE 1 is a circuit block diagram of a clock change circuit consistent with

17 an embodiment of the present invention.

18 FIGURE 2 is a timing diagram illustrating the operation of the circuit of

19 FIGURE 1.

20 FIGURE 3 is a flow chart of a process consistent with an embodiment of the

21 present invention.

22 FIGURE 4 is a circuit diagram of an alternative logic circuit arrangement for

23 an embodiment of the present invention.

24 FIGURE 5 is another circuit diagram of another alternative logic circuit

25 arrangement for another embodiment of the present invention.

26

27 **DETAILED DESCRIPTION OF THE INVENTION**

28 In the following detailed description of the present invention, numerous

29 specific details are set forth in order to provide a thorough understanding of the

1 present invention. However, it will be recognized by one skilled in the art that the
2 present invention may be practiced without these specific details or with
3 equivalents thereof. In other instances, well known methods, procedures,
4 components, and circuits have not been described in detail as not to unnecessarily
5 obscure aspects of the present invention.

6

NOTATION AND NOMENCLATURE

8 Some portions of the detailed descriptions which follow are presented in
9 terms of procedures, steps, logic blocks, processing, and other symbolic
10 representations of operations on data bits that can be performed on computer
11 memory. These descriptions and representations are the means used by those
12 skilled in the data processing arts to most effectively convey the substance of their
13 work to others skilled in the art. A procedure, computer executed step, logic block,
14 process, etc., is here, and generally, conceived to be a self-consistent sequence
15 of steps or instructions leading to a desired result. The steps are those requiring
16 physical manipulations of physical quantities.

17 Usually, though not necessarily, these quantities take the form of electrical
18 or magnetic signals capable of being stored, transferred, combined, compared, and
19 otherwise manipulated in a computer system. It has proven convenient at times,
20 principally for reasons of common usage, to refer to these signals as bits, values,
21 elements, symbols, characters, terms, numbers, or the like.

22 It should be borne in mind, however, that all of these and similar terms are
23 to be associated with the appropriate physical quantities and are merely convenient
24 labels applied to these quantities. Unless specifically stated otherwise as apparent
25 from the following discussions, it is appreciated that throughout the present
26 invention, discussions utilizing terms such as "processing" or "computing" or
27 "translating" or "calculating" or "determining" or "storing" or "issuing" or
28 "recognizing" or the like, refer to the action and processes of a computer system,
29 or similar electronic computing device, that manipulates and transforms data
30 represented as physical (electronic) quantities within the computer system's

1   registers and memories into other data similarly represented as physical quantities
2   within the computer system memories or registers or other such information
3   storage, transmission or display devices.
4
5   **METHOD AND CIRCUIT FOR ALLOWING A MICROPROCESSOR TO CHANGE**
6   **ITS OPERATING FREQUENCY ON-THE-FLY IN ACCORDANCE WITH THE**
7   **INVENTION**
8   While this invention is susceptible of embodiment in many different forms,
9   there is shown in the drawings and will herein be described in detail specific
10   embodiments, with the understanding that the present disclosure is to be
11   considered as an example of the principles of the invention and not intended to limit
12   the invention to the specific embodiments shown and described. In the description
13   below, like reference numerals are used to describe the same, similar or
14   corresponding parts in the several views of the drawings.
15   Referring now to **FIGURE 1**, a circuit 100 for effecting the processor
16   controlled clock speed manipulation of certain embodiments of the present
17   invention is illustrated. A master clock 104, such as a crystal oscillator or other
18   oscillator, provides a master clock signal 108 to a clock generator circuit 112. The
19   clock generator circuit 112 produces a plurality of clock signals 114, 116 through
20   120 as illustrated. This can be readily accomplished using a series of flip flops with
21   an output of the flip flops being tapped to provide each of the available clock
22   signals at lines 114, 116 through 120. In certain preferred embodiments, eight
23   such signals are provided with eight varying frequencies. The clock signals 114,
24   116 through 120 are provided to a current speed switch 124 and to a new speed
25   switch 128. The current speed switch selects one of the input clock signals 114,
26   116 through 120 as its output under control of a current speed signal 130. The
27   current speed signal 130 is retained in a latch, referred to herein as current speed
28   latch 132. The current speed latch 132 is a three bit latch in accordance with the
29   current invention to provide for a three bit signal 130 that can select one of the eight

1   input clock signals 114, 116 through 120, but of course this is not to be limiting

2   since the size of the latch and the number of generated clock frequencies can be

3   readily varied by those skilled in the art.

4   The new speed switch 128 also selects one of the input clock signals 114,

5   116 through 120 as an output thereof under control of a new speed signal 136. The

6   new speed signal 136 is stored in a new speed register 140 under the direction of

7   the microcontroller's processor 144. Again, in the preferred embodiment of eight

8   clock signals, a three bit new speed control signal 136 is used and is stored in a

9   three bit new speed register 140. The new speed register 140 stores a clock speed

10   select signal generated by the processor 144 of the microcontroller and

11   communicated to the new speed register 140 over the processor data bus 146.

12   The selected current speed at switch 124 is provided as an output at 150 to clock

13   the processor 144 and any other circuitry that needs to be driven by this clock

14   signal. The clock signal 150 is also applied to a phase shifter circuit 154, which in

15   the preferred embodiment may simply be a fixed delay, to produce a phase shifted

16   version of the current clock at 158. The signal for the current clock is designated

17   CLK appearing at 150 and the phase shifted clock at 158 is designated CLKP. In

18   a similar manner, under direction of the new speed signal 136, new speed switch

19   128 selects one of the input clocks 114, 116 through 120 as an output at 160 which

20   is designated to be signal NEW. The signal NEW at 160 is also applied to a phase

21   shifter at 164, which in the current embodiment may also be a simple fixed delay,

22   to produce the signal at 168 designated NEWP which is a phase shifted version of

23   the new clock.

24   The new speed signal at 136 is also applied as an input to the current speed

25   latch 132. However, the new speed is only latched into the current speed latch

26   132, thereby changing the current speed produced by current speed switch 124, as

27   a result of receipt of a latch signal at 174 produced by a logic circuit. In the

28   preferred embodiment, the logic circuit comprises a simple five input NOR gate 180

29   that receives the clock signals CLK, CLKP, NEW and NEWP as well as an I/O

30   write signal produced by the processor 144.

1   The NOR gate implementation 180 of the present invention should not be
2   considered limiting since other logic configurations can also be used. However, the
3   NOR gate 180 is a very simple implementation for the present invention occupying
4   very small amounts of the microcontroller's die area. The I/O write signal 184 from
5   processor 144 is a normally low logic state in this embodiment, but the processor
6   toggles to a logic high state briefly and then returns to the low state to indicate that
7   the frequency change should be carried out. At a time just prior to (or simultaneous
8   with) generating the low going transition of the I/O write signal 184, the processor
9   144 stores the new clock speed in new speed register 140 via the processor data
10   bus 146 and the new speed is directed to the new speed switch 128 by new speed
11   signal 136.

12   Thus, at the time of the I/O write signal, the logic gate 180 is receiving both
13   of the current clocks as well as both of the proposed new clocks. In the current
14   implementation, once the I/O write signal returns to a logical low state, a latch
15   signal 174, latching the new speed into the current speed latch132, is produced the
16   next time all four of the clock signals (CLK, CLKP, NEW and NEWP) are at a logic
17   low level. At this point, the low going transition of latch signal 174 causes the
18   current speed latch 132 to accept the new speed signal 136 as its stored value
19   produced at 130.

20   Referring now to **FIGURE 2**, a timing diagram illustrates the events leading
21   to a change in clock speed in one embodiment. The master clock 108 is shown
22   at the top for reference. The new clock signal NEW at 160 and phase shifted new
23   clock signal NEWP at 168 differ by only a small delay in the new clock signal 168.
24   At time T0 both the new clock signals NEW and NEWP and the current clock
25   signals CLK and CLKP are being produced at the output of switches 128 and 124
26   and phase shifters 164 and 154. At this time, as a result of any previous clock
27   speed change or because it is the initial clock speed, CLK is the same as NEW
28   and CLKP is the same as NEWP. At time T1, the I/O write signal toggles from its
29   normal logic low state to a logic high state in preparation for a frequency change.
30   In this embodiment, the time T1 should be at approximately the same time as the

1   selection of a new speed at new speed register 140 and new speed switch 128, but

2   this is not to be limiting as long as all four clocks are present at the NOR gate 180

3   at time T2. At T1, it should be noted, it is possible for the signals NEW and NEWP

4   to "glitch" as shown since a new clock signal is being switched at switch 128.

5   However, no such transition is occurring at switch 124 as evidenced by no change

6   in the signals CLK and CLKP at time T1.

7   At time T2, the transition from logic high to logic low of the I/O write signal

8   enables the logic gate 180 to make an output transition to latch the new speed into

9   the current speed latch 132 as soon as all of the input signals are at a logic low as

10   shown by latch signal 174. Once this occurs, signals NEW and CLK are set equal

11   as are signals NEWP and CLKP as shown at time T3 and beyond. It is noted that

12   at times subsequent to time T3, the latch signal 174 periodically pulses in this

13   embodiment whenever all of the input signals to logic gate 180 are at a logic low.

14   However, at this time, the new speed signal 136 is equal to the current speed

15   signal at 130 and no transition or glitching of the clocks occurs.

16   The process just described can be described as a process in accordance

17   with the flow chart of **FIGURE 3** as process 300 starting at 302. If a frequency

18   change is to occur at 306, the new clock frequency is stored in the new speed

19   register 140 to set the value of the new speed at switch 128 at 310. The various

20   states of the current clock and the new clock and their phase shifted versions are

21   examined at 312 until the appropriate states of the clocks coincide at 318. Once

22   this occurs, the new speed is latched into the current speed latch at 322 and the

23   current clock is switched to the new clock according to the contents of the current

24   speed latch at 330. The process then returns to 306 until the next frequency

25   change.

26   Those skilled in the art will appreciate many variations are possible for the

27   present invention. For example, although the present embodiment utilizes a simple

28   NOR gate 180 as the decision making logic that initiates the speed change, in

29   many embodiments it is only required that the signals CLK and NEW be equal as

30   well as the signals CLKP and NEWP be equal for the transition to occur without

1 producing glitches and the like. In some embodiments, the there may be an

2 advantage in the logic circuit detecting either high or low logic states, and those

3 skilled in the art can readily adapt the current design to this preference without

4 departing from the invention.

5 FIGURE 4, illustrates a circuit that can be used to detect a condition of all

6 clock signals being at a logic high and equal, with the I/O write signal being

7 essentially the same as the previous embodiment. This circuit can generally be

8 used instead of the NOR gate 180 if detection of logic high levels is desirable. In

9 this embodiment, the signals NEW and CLK are compared at a NAND gate 402

10 while NEWP and CLKP are compared at NAND gate 404. The output of gates 402

11 and 404 are applied along with the I/O write signal to a NOR gate 408 the output

12 of which produces the latch signal. It is noted that the circuit arrangement 400 of

13 FIGURE 4 may produce a change in clock frequency at a different time than in the

14 previous example, that is, when all of the signals are at a logic high state rather

15 than a logic low state, but in general this is of little consequence. Those skilled in

16 the art will appreciate that many other logic arrangements are possible to

17 implement the clock change of the present invention without departing from the

18 present invention. In another embodiment having similar results, a single four input

19 NAND gate can substitute for the two NAND gates 402 and 404. Similarly, by

20 substitution of an AND gate for NOR gate 408, an I/O write signal of inverted

21 polarity could be used.

22 Referring now to FIGURE 5, another embodiment of a logic circuit suitable

23 for replacing NOR gate 180 is illustrated in which exclusive OR gates 502 and 504

24 respectively receive signals CLK and NEW at gate 502 and CLKP and NEWP at

25 gate 504. Their outputs are again combined with the I/O write signal at NOR gate

26 508 to produce the latch signal as an output. In the embodiment shown as circuit

27 500 at FIGURE 5, whenever the signal CLK and NEW are equal and the signal

28 CLKP and NEWP are equal and the I/O write signal is low, the latch signal is

29 produced. Thus, the circuit of FIGURE 5, will institute a change in the frequency

1   if, for example, the two clock signals CLK and NEW are high while the phase

2   shifted clock signals CLKP and NEWP are low (but equal). Similarly, if signals

3   CLK and NEW are low and signals CLKP and NEWP are high the latch signal can

4   be generated. In this example the only requirement for generating the latch signal

5   imposed upon the clock signals is that the clock signals are equal and the phase

6   shifted clock signals are equal. Many other variations of circuits to accomplish

7   similar functions will occur to those skilled in the art without departing from the

8   present invention.

9   In accordance with the preferred embodiment, the master clock may be a

10   24 or 48MHz clock and the phase shift may be accomplished by a fixed delay of

11   approximately 21 nanoseconds. However, this is not to be considered limiting since

12   variable or proportional delays could also be used. Since the I/O write signal 184

13   and the clock speed select signal sent over bus 146 originate at the processor, the

14   operational speed of the processor 144 can be adjusted under program control

15   based on whatever conditions can be programmed into the microcontroller's

16   processor 144. Moreover, the present arrangement occupies very little area on the

17   microcontroller die and provides a simple solution to the problem of changing clock

18   speeds.

19   While the invention has been described in conjunction with specific

20   embodiments, it is evident that many alternatives, modifications, permutations and

21   variations will become apparent to those skilled in the art in light of the foregoing

22   description. Accordingly, it is intended that the present invention embrace all such

23   alternatives, modifications and variations as fall within the scope of the appended

24   claims.

25   What is claimed is:

26